

MXR

DUNLOP MANUFACTURING INC.
P.O. BOX 846 BENICIA, CA 94510
U.S.A. JIMDUNLOP.COM



OCTAVIO

OCTAVIO® JHM2

DESCRIPTION

- The octave up fuzz design that Jimi used to make rock history
- Pedalboard-friendly housing
- Limited edition finish featuring art by legendary rock artist John Van Hamersveld

POWER

The JHM2 Jimi Hendrix 70th Anniversary Tribute Series Octavio can be powered by one 9 volt battery (accessed via the bottom of the pedal), a Dunlop ECB003 AC adapter (ECB003E in Europe) or a DC Brick™ series power supply.

CONTROLS

- LEVEL knob controls overall volume of effect
- FUZZ knob controls amount of octave up fuzz
- FOOTSWITCH toggles effect on/bypass (indicated by blue LED)

DIRECTIONS

- Run a cable from your guitar to the Octavio's Input jack and run another cable from the Octavio's Output jack to your amplifier.
- Start with LEVEL and FUZZ controls at 12 o'clock.
- Turn the effect on by depressing the footswitch.
- Rotate LEVEL knob clockwise to increase overall volume or counterclockwise to decrease it.
- Rotate FUZZ knob clockwise to increase amount of octave up fuzz or counterclockwise to decrease it.

SAMPLE SETTINGS

PURPLE HAZE



ONE RAINY WISH



SPECIFICATIONS

Input Impedance	
Max Fuzz	187k Ω
Min Fuzz	15k Ω
Output Impedance	
Max Volume	1.5k Ω
Mid Volume	50k Ω
Max Output	1.7 Vpp
Gain Range	8dB to 37dB
Bypass	True Hardwire
Current Draw	5.9mA
Power Requirement	9 volts DC

