

POWER BLOCK

Manual

English

POWER SUPPLY

The RockBoard[®] Power Block comes with a regulated 18V power adaptor, that can handle up to 2000 mA. It is built to handle 100 to 240V input at 47 to 63 Hz.

CAUTION:

If you use a proprietary power adaptor, make sure it meets the above mentioned input and output data to avoid overheating and damage of the unit.

- 18V input jack; plug in DC power adapter here
- (2) 9V output jacks with individual LEDs indicating that short circuited pedals are attached
- ③ Blue LED indicating if unit is powered
- (4) 2 x 18 Volt output jacks for pedals with 18 Volt power supply

DESCRIPTION & ACCESSORY

- Simultaneous powering of 8 x 9V and 2 x 18V pedals without loss of signal quality.
- 8 red LEDs indicate short-circuitry for each 9V-port individually.
- Accessories: AC-Adaptor, connection cables for each port.



CONNECTIONS & USAGE

- 1. Plug the included AC adaptor into the units input port.
- 2. Plug the AC adaptor into the wall outlet. The blue LED will light up to indicate correct powering.
- Connect your pedals to the appropriate output ports with the included connection cables.
- If one of the red LEDs lights up, a pedal is short circuited. Refer to the wiring diagram below to connect the pedals with the correct polarity.
- 5. Power handling: 1 200 mA in sum for the eight 9V outputs and 800 mA in sum for the two 18V outputs. Total Power handling: 2 000 mA



Use standard industry 5.5 x 2.1 mm jacks with positive barrel and negative tip wiring.



USA DISTRIBUTION: Framus & Warwick Music USA, Inc. | info@rockboard.net | 629.202.6790 CHINESE DISTRIBUTION: Warwick Music Equipment Trading (Shanghai) Co. Ltd. | info@warwick.cn | +862134060110 NORTH EUROPEAN DISTRIBUTION: www.rockboard.de | info@rockboard.de | www.w-distribution.de | www.facebook.com/warwickmusicdistribution

Headquarters: Warwick GmbH & Co. Music Equipment KG | 08258 Markneukirchen / Germany | +49 (0) 37422 / 555 - 0 Family Owned • Solar Powered • Sustainably Manufactured in a Green Environment