

THE ORIGINAL SINCE 1967.

CRY BABY

LIVE TO PLAY LIVE®



JIMDUNLOP.COM

92503003528revC

# GCB95 ORIGINAL CRY BABY®

## POWER

The Original Cry Baby® can be powered by one 9 volt battery (accessed via the bottom of the pedal), a Dunlop ECB003 AC adapter (ECB003E in Europe) or a Dunlop DCB10 DC Brick power supply.

## SETUP INSTRUCTIONS

- Run a shielded instrument cable from your guitar to the GCB95's Instrument jack.
- Run another shielded instrument cable from the GCB95's Amplifier jack into your amplifier input.
- Turn on the amplifier and begin playing.
- To turn the pedal on/off, push the toe of the pedal down until you feel a "click."
- By rocking your foot back and forth on the pedal, you can instantaneously change the effect that the Original Cry Baby has on the tone of your instrument.

## SPECIFICATIONS

### Impedance

Input	800 k $\Omega$
Output	10 k $\Omega$

### Resonant Frequency

Heel Down	350 Hz - 450 Hz
Toe Down	1.5 kHz - 2.5 kHz

### Maximum Level

Input	-8.0 dBV
Output	+10 dBV

### Maximum Gain

Heel Down	+19.5 dB
Toe Down	+19.0 dB

### Signal to Noise Ratio\*

Heel Down	98 dB
Toe Down	89 dB

Current Draw	900 $\mu$ A
--------------	-------------

\*A-weighted, OdBV = 1V<sub>RMS</sub>

